

## OPTICAL RETURN LOSS TEST SET

# BRT-320A

NETWORK TESTING—OPTICAL



### Features Sous-titre

- Built-in thermoelectrically cooled (TEC) laser(s)
- Range of 0 dB to -70 dB
- Quick and easy to operate
- Rugged, field-ready
- Stores up to 300 readings

### Fast Stabilization

EXFO's BRT-320A is a field-ready return loss test set offered in five configurations: 1310 nm, 1550 nm or 1625 nm; dual-wavelength 1310/1550 nm or 1550/1625 nm. All come equipped with rapidly stabilizing TEC lasers and low-drift photodetectors to ensure constant optical return loss (ORL) measurements year after year.

### Built-In User-Friendliness

Use the BRT-320A to read backreflection from 0 dB to -70 dB and easily store up to 300 readings in a non-volatile memory. ORL readings appear directly on the large, backlit LCD. An ORL zero function accounts for incidental backreflections before the point of measurement and complies with Bellcore optical continuous wave reflectometer (OCWR) requirements. In User Calibration mode, you can calibrate the unit to a known reflection. Other features include three-way powering (rechargeable NiCd battery pack, 9 V battery, AC adapter/charger), 0.01 dB resolution,  $\pm 0.1$  dB linearity, internal InGaAs detector, low-battery indicator and a protective holster with shoulder strap.

### Reveal Return Loss Problems

Many digital and analog fiber systems require ORL characterization. ORL along a fiber span is a combination of Rayleigh scattering and Fresnel reflections. Together, these phenomena can reduce fiber system performance and increase bit error rate (BER) by degrading transmitter stability. The BRT-320A measures cumulative link return loss and individual component reflectance to reveal potential ORL problems before they seriously affect your applications.

### Versatile

The BRT-320A is ideal for local and long-distance Telco, CATV, utility, broadband and transmission equipment manufacturing applications. These environments often require complete network ORL characterization and component reflectance verification. The BRT-320A also functions as a stable, continuous-wavelength light source for attenuation measurements. Other applications include fiber component and cable manufacturing.

## SPECIFICATIONS <sup>a</sup>

Model	BRT-320A-02BLC-58	BRT-320A-03BLC-58	BRT-320A-23BLC-58	BRT-320A-04BLC	BRT-320A-34BLC
Wavelength (nm)	1310 ± 15	1550 ± 15	1310/1550 ± 15	1625 ± 15	1550/1625 ± 15
Spectral width (rms) <sup>b</sup> (nm)	< 5	< 5	< 5	< 5	< 5
Output power stability (dB)					
15 minutes <sup>c</sup>	± 0.01	± 0.01	± 0.02	–	–
1 hour <sup>d</sup>	± 0.05	± 0.05	± 0.06	–	–
Temperature stability <sup>e</sup> (dB)	± 0.2	± 0.2	± 0.3	–	–
Reflection range (dB)	0 to –70	0 to –70	0 to –70	0 to –70	0 to –70
Display resolution <sup>f</sup> (dB)	0.01	0.01	0.01	0.01	0.01
Linearity <sup>g</sup> (dB)	± 0.1	± 0.1	± 0.1	± 0.1	± 0.1
Uncertainty (accuracy) <sup>g</sup> (dB)	± 0.5	± 0.5	± 0.5	± 0.5	± 0.5
Minimum output power (dBm)	–6.5	–6.5	–7.5	–3	–9/–7
Polarization sensitivity <sup>h</sup> (dB)	± 0.15	± 0.15	± 0.15	± 0.15	± 0.15

## GENERAL SPECIFICATIONS <sup>a</sup>

Size (H x W x D)		21 cm x 11 cm x 5 cm	(8 3/4 in x 4 1/2 in x 2 in)
Weight unit	0.8 kg	(1 3/4 lb)	
shipping	2.5 kg	(5 1/2 lb)	
Temperature			
operating		–10 °C to 40 °C	(14 °F to 104 °F)
storage	–30 °C to 60 °C	(–22 °F to 140 °F)	
Relative humidity		0 % to 95 % non-condensing	
Power	Built-in NiCd batteries (10 hours of operation), 9 V alkaline battery backup, AC adapter/charger		

## ORDERING INFORMATION

### BRT-320A-XXBLC-XX

#### Source code ■

02BLC = 1310 nm TEC laser  
03BLC = 1550 nm TEC laser  
23BLC = 1310/1550 nm TEC laser  
04BLC = 1625 nm TEC laser  
34BLC = 1550/1625 nm laser

#### Connector code ■

EA-EUI-28 = APC/DIN 47256  
EA-EUI-89 = APC/FC narrow key  
EA-EUI-91 = APC/SC  
EA-EUI-95 = APC/E-2000

With EA, a standard test jumper is provided:

EUI-28 = TJ-B86-86  
EUI-89 = TJ-B58-58  
EUI-91 = TJ-B88-88  
EUI-95 = TJ-B96-96

Example: BRT-320A-02BLC-EA-EUI-89

## STANDARD ACCESSORIES

User Guide, AC adapter/charger, NiCd batteries, 9 V alkaline battery, carrying case, protective holster, shoulder strap, mandrel tool, complimentary test jumper, and Certificate of Compliance.

## SAFETY

This product complies with 21 CFR 1040.10 and IEC 60825-1: Ed 1.1 1998:  
CLASS 1 LASER PRODUCT

## NOTES

- Characterized at 23 °C ± 2 °C (70 °F ± to 77 °F).
- rms = root mean square.
- Typical, after 5-minute warmup (measurement mode activated only after warmup).
- Typical, after a 15 minute warmup.
- For temperatures ranging from –10 °C to 40 °C (14 °F to 104 °F).
- From 0 dB to –30 dB.
- For reflection measurements from –15 dB to –50 dB.  
Connector on measurement port must cause less than –50 dB of reflection to maintain resolution.
- Typical.

### Rugged Handheld Solutions

- OPTICAL**
  - OLTs
  - Power meters
  - Light sources
  - Talk sets
- COPPER ACCESS**
  - ADSL/ADSL2+, SHDSL, VDSL test sets
  - VoIP and IPTV test sets
  - Ethernet test sets
  - POTS test sets

### Platform-Based Solutions

- OPTICAL FIBER**
  - OTDRs
  - OLTs
  - ORL meters
  - Variable attenuators
- DWDM TEST SYSTEMS**
  - OSAs
  - PMD analyzers
  - Chromatic dispersion analyzer
- TRANSPORT AND DATACOM**
  - Next Generation SONET/SDH and OTN testers
  - SONET/DSn (DS0 to OC-192) testers
  - SDH/PDH (64 kb/s to STM-64) testers
  - T1/T3, E1 testers
  - 10/100M and Gigabit Ethernet testers
  - Fibre Channel testers
  - 10 Gigabit Ethernet testers

Find out more about EXFO's extensive line of high-performance portable instruments by visiting our website at [www.EXFO.com](http://www.EXFO.com).

EXFO Corporate Headquarters > 400 Godin Avenue, Quebec City (Quebec) G1M 2K2 CANADA | Tel.: 1 418 683-0211 | Fax: 1 418 683-2170 | [info@EXFO.com](mailto:info@EXFO.com)

Toll-free: 1 800 663-3936 (USA and Canada) | [www.EXFO.com](http://www.EXFO.com)

<b>EXFO Montreal</b>	2650 Marie-Curie	St-Laurent (Quebec) H4S 2C3 CANADA	Tel.: 1 514 856-2222	Fax: 1 514 856-2232
<b>EXFO Toronto</b>	160 Drumlin Circle	Concord (Ontario) L4K 3E5 CANADA	Tel.: 1 905 738-3741	Fax: 1 905 738-3712
<b>EXFO America</b>	3701 Plano Parkway, Suite 160	Plano, TX 75075 USA	Tel.: 1 800 663-3936	Fax: 1 972 836-0164
<b>EXFO Europe</b>	SOUTHAMPTON > Omega Enterprise Park, Electron Way	Chandlers Ford, Hampshire S053 4SE ENGLAND	Tel.: +44 2380 246810	Fax: +44 2380 246801
<b>EXFO Asia</b>	151 Chin Swee Road, #03-29 Manhattan House	SINGAPORE 169876	Tel.: +65 6333 8241	Fax: +65 6333 8242
<b>EXFO China</b>	No.88 Fuhua, First Road Central Tower, Room 801, Futian District Beijing New Century Hotel Office Tower, Room 1754-1755 No. 6 Southern Capital Gym Road	Shenzhen 518048, CHINA  Beijing 100044 P.R. CHINA	Tel.: +86 (755) 8203 2300  Tel.: +86 (10) 6849 2738	Fax: +86 (755) 8203 2306  Fax: +86 (10) 6849 2662

EXFO is certified ISO 9001 and attests to the quality of these products. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. All of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit [www.EXFO.com/recycle](http://www.EXFO.com/recycle). However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.

For the most recent version of this spec sheet, please go to the EXFO website at <http://www.EXFO.com/specs>

In case of discrepancy, the Web version takes precedence over any printed literature.